

MEGNATE ANTENNA 5dbi



Frequency Range	698MHz-2700MHz, 2400 – 2483 MHz	Height	265 mm
Impedance	50 Ohm	Diameter of Chassis	Dia. 40 mm
VSWR	less than 2	Termination	SMA male
Gain	5 dbi	Coaxial Cable	RG-174
Polarization	Vertical	Length of Cable	3/5/7mtrs
Radiation	Omni		
Max. Power Input-watts	50 W		

Regd Add: F36a, Street No.8, Vishwas Park, Uttam Nagar, New Delhi - 110059

Tel: +91-9716582707 , +91-8810686612

Email: info@agartel.com , sales@agartel.com

web: www.agartel.in / www.rfcableconnector.in
